



03			
02			
01			
00			
Rev	Description	Date	APVD

Revision History

Power Supply: 110-120V AC or 220-240V AC

- C.S: Control Switch
- P.E: Protective Earth
- H: Heater
- HT: Heater Thermostat
- MT: Motor Thermostat
- M: Motor
- LS1: Limit Switch for OPEN (3A/250V AC)
- LS2: Limit Switch for CLOSE (3A/250V AC)
- LS3: Limit Switch for Handwheel (3A/250V AC)

Notes:

- 1) "N" connects to 1, "L" connects to 7.
- 2) "L" connects to 3 for "OPEN".
- 3) "L" connects to 4 for "CLOSE".
- 4) Using less than 3A current for "A,B,C,D,E,F".
- 5) Wiring is shown with Actuator Fully Closed.
- 6) **Applicable to Actuator models iVL-C, D.**



Innovative Actuation Incorporated

1-215 Traders Blvd. Mississauga, Ontario Canada www.ivact.com

DESCRIPTION:

110/220V AC ON/OFF with Heater and Thermostat 75% Duty

WIRING DIAGRAM CODE: **LB** DATE: **MAR. 07/2023**

WIRING DIAGRAM NO.: **L-2AN2NNNN-2**