



03			
02			
01			
00			
Rev	Description	Date	APVD

Revision History

Power Supply: 24V DC

P.E: Protective Earth
H: Heater
HT: Heater Thermostat
MT: Motor Thermostat
M: Motor
LS1: Limit Switch for OPEN (5A/250V AC)
LS2: Limit Switch for CLOSE (5A/250V AC)
LS3: SPDT Auxiliary Limit Switch (5A/250V AC)
LS4: SPDT Auxiliary Limit Switch (5A/250V AC)
TS: Torque Switches (optional)

Notes:

- 1) "-" connects to 1, "+" connects to 7.
- 2) "+" connects to 3 for "OPEN".
- 3) "+" connects to 4 for "CLOSE".
- 4) Using less than 5A current for "A,B,C,D,E,F".
- 5) Using battery to supply for DC units.
- 6) #8 connects to #9 for current output signal (4-20mA) and #8 connects to #10 for voltage output signal (2-10V).
- 7) Wiring is shown with Actuator Fully Closed.
- 8) **Applicable to Actuator models iVQ-O to R.**

Fully Open	A to C
Fully Close	D to F



Innovative Actuation Incorporated

1-215 Traders Blvd. Mississauga, Ontario Canada www.ivact.com

DESCRIPTION:
24V DC ON/OFF with Heater, Thermostat,
Auxiliary Switches and 4-20mA Feedback
50% Duty

WIRING DIAGRAM CODE: QD DATE: JAN. 07/2021

WIRING DIAGRAM NO.: Q-1CN21N3N-2