



03			
02			
01			
00			
Rev	Description	Date	APVD

Revision History

Power Supply: 24V AC or DC

P.E: Protective Earth
H: Heater
HT: Heater Thermostat
MT: Motor Thermostat
M: Motor
LS1: Limit Switch for OPEN (3A/250V AC)
LS2: Limit Switch for CLOSE (3A/250V AC)
LS3: SPDT Auxiliary Limit Switch (3A/250V AC)
LS4: SPDT Auxiliary Limit Switch (3A/250V AC)
TS: Torque Switches (optional)

- Notes:
- 1) "N/-" connects to 1, "L/+" connects to 7.
 - 2) "L/+" connects to 3 for "OPEN".
 - 3) "L/+" connects to 4 for "CLOSE"
 - 4) Using less than 3A current for "A,B,C,E,F"
 - 5) JP5 : MODE (2-10V), J2 : Signal Output (2-10V).
 - 6) Wiring is shown with Actuator Fully Closed.
 - 7) **Applicable to Actuator models iVQ-C, D.**



Innovative Actuation Incorporated

1-215 Traders Blvd. Mississauga, Ontario Canada www.ivact.com

DESCRIPTION:
24V AC/DC ON/OFF with Heater, Thermostat,
Auxiliary Switches and 4-20mA Feedback
75% Duty

WIRING DIAGRAM CODE: **QJ** DATE: **JAN. 07/2021**

WIRING DIAGRAM NO.: **Q-1EN21N3N-1**